

Control Gear- CG.ET 12VAC.070ST

Eeectronic Transformer

Replaces:

Constan Current and DC Voltage power supplies

Applications:

12V AC lighting installations

Warranty (Yrs.)

5



Control Gear ET 12VAC.070 is an Eeectronic Transformer, designed to drive low voltage AC LED based luminaires such as VisiLite. ET 12VAC.070 is a robust and dimmable power supply and can be used to run several AC LED luminants in parallel.

IP Rating	20	Beam Angle (°FWHM)	
System Power (W)	70	Flux (Lm)	
System efficacy (Lm/W)	0	CRI (Ra4)	
Input Voltage (V)	220- 240v	CCT (K)	
Input frequency (Hz)	50H	Life Expectancy (Hrs.)	> 50000
Power Factor (cos phi)	>0.9	Lx @ 1m	0
Operating temp. (°C)	10 ~ 40	2m	
Storage temp. (°C)	0 ~40	3m	
Weight (gr)	150	Illuminated area (m)@ 1m	0.00
Dimensions (mm): LxWxH	100x 40x 30	2m	0.00
		3m	0.00